




Hall of Fame Mini Reverb

English manual – 2015-09-01

Table of contents

Important safety instructions	1	Inputs, outputs and controls	13
Caution	2	Power / Switching the effect on and off	14
Service	2	Footswitch	14
Warning	2	Audio in and out	14
EMC/EMI	2	Effect controls	15
Explanation of graphic symbols	3	Reverb types	15
Before you begin	4	Maintenance	17
About this manual	5	Updating the firmware	18
Getting support	5		
 		Frequently asked questions	19
About this pedal	6	Frequently asked questions about	
Hall of Fame Mini Reverb	7	TonePrint pedals	20
True Bypass	7		
 		Links	21
TonePrint	8	TonePrint resources	22
What are TonePrints?	9	Support resources	22
Transferring TonePrints to your pedal		TC Electronic on...	22
using the TonePrint app	9		
Editing TonePrints with TonePrint Editor	10		
 		Technical specifications	23
Setup	11		
Ready...	12		
Set...	12		
Play!	12		

Important safety instructions

1. Read these instructions.
2. Keep these instructions.
3. Heed all warnings.
4. Follow all instructions.
5. Do not use this apparatus near water.
6. Clean only with a dry cloth.
7. Do not block any ventilation openings. Install in accordance with the manufacturer's instructions.
8. Do not install near any heat sources such as radiators, heat registers, stoves, or other apparatus (including amplifiers) that produce heat.
9. Do not defeat the safety purpose of the polarized or grounding-type plug. A polarized plug has two blades with one wider than the other. A grounding-type plug has two blades and a third grounding prong. The wide blade or the third prong is provided for your safety. If the provided plug does not fit into your outlet, consult an electrician for replacement of the obsolete outlet.
10. Protect the power cord from being walked on or pinched, particularly at plugs, convenience receptacles, and the point where they exit from the apparatus.
11. Only use attachments/accessories specified by the manufacturer.
12. Use only with a cart, stand, tripod, bracket, or table specified by the manufacturer, or sold with the apparatus. When a cart is used, use caution when moving the cart/apparatus combination to avoid injury from tip-over. 
13. Unplug this apparatus during lightning storms or when unused for long periods of time.

14. Refer all servicing to qualified service personnel. Servicing is required when the apparatus has been damaged in any way, such as power-supply cord or plug is damaged, liquid has been spilled or objects have fallen into the apparatus, the apparatus has been exposed to rain or moisture, does not operate normally, or has been dropped.

Caution

You are cautioned that any change or modifications not expressly approved in this manual could void your authority to operate this equipment.

Service

All service must be performed by qualified personnel.

Warning

To reduce the risk of fire or electric shock, do not expose this apparatus to rain or moisture and objects filled with liquids, such as vases, should not be placed on this apparatus.

Do not install this device in a confined space.

EMC/EMI

Electromagnetic compatibility/
Electromagnetic interference

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules.

These limits are designed to provide reasonable protection against harmful interference in residential installations. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- ▶ Reorient or relocate the receiving antenna.
- ▶ Increase the separation between the equipment and receiver.
- ▶ Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- ▶ Consult the dealer or an experienced radio/TV technician for help.

For customers in Canada

This Class B digital apparatus complies with Canadian ICES-003.

Cet appareil numérique de la classe B est conforme à la norme NMB-003 du Canada.

Explanation of graphic symbols



The lightning bolt triangle is used to alert the user to the presence of uninsulated “dangerous voltages” within the unit’s chassis that may be of sufficient magnitude to constitute a risk of electric shock to humans.



The exclamation point triangle is used to alert the user to presence of important operating and service instructions in the literature accompanying the product.

Before you begin

About this manual

Use this manual to learn how to set up and operate your TC product.

To get the most from this manual, please read it from start to finish, or you may miss important information.

This manual is only available as a PDF download from the TC Electronic website.

Of course, you can print this manual, but we encourage you to use the PDF version, which has both internal and external hyperlinks. For example, clicking the logo in the upper left corner of each page will take you back to the table of contents.

To download the most current version of this manual, visit

tcelectronic.com/support/manuals/

Getting support

If you still have questions about the product after reading this manual, please get in touch with TC Support:

tcelectronic.com/support/

Enjoy your TC product!

About this pedal

Thank you for spending your hard-earned money on this TC Electronic product! We have done our best to ensure that it will serve you for many years to come, and we hope that you will enjoy using it.

Hall of Fame Mini Reverb

TC Electronic is synonymous with some of the best sounding reverbs out there. Think of a song with reverb on it that you have heard in the last 20 years – and chances are it's us. We collected the iconic reverb sounds you know and love into a neat little package that simply sounds so insanely good – you just got to try it.

Range is everything

Hall Of Fame Mini allows you to experiment and play with reverb the way you see fit. With ten different reverb types to choose from, you'll never be without a great reverb sound.

Hall Of Fame Mini Control is the verb

It's amazing that just three controls (Decay, Tone and Level) can give such a wide range of tonal options – bright and springy, warm and bouncy or gigantic dark reflections... It's all there in spades – and then some.

True Bypass

Here at TC, we have a simple philosophy: When you are using one of our products, you should hear something great – and if you don't, you shouldn't hear it at all. This is why this pedal sports **True Bypass**. When it is bypassed, it is really off and has zero influence on your tone, resulting in optimum clarity and zero loss of high-end.

You will also be delighted to hear (*literally*) that this TC Electronic effect pedal will let your dry, unprocessed sound pass without ever converting it to digital – keeping your original tone pure and without any latency. This feature is called **analog dry-through**.

TonePrint

This TC Electronic product supports TonePrints. To learn more about TonePrints, go to tcelectronic.com/toneprint/

What are TonePrints?

When you look at your TC Electronic effect pedal, you'll only see a few knobs. Actually, for some pedals, it's just one knob. So – one knob, one function, right?

Actually, there's a lot more to it than meets the eye.

Star-tweaked signature sounds

When TC Electronic builds an effect pedal, the relationship between its controls and many parameters “under the hood” are defined by developers, musicians and product specialists who live and breathe sound. This gives you an excellent starting point: a great-sounding pedal with well-balanced controls.

But wouldn't it be cool to have world-famous guitar players – guys like [Paul Gilbert](#), [Guthrie Govan](#), [John Petrucci](#) or [Steve Vai](#) – virtually rewire your reverb pedal, defining what should happen “behind the scenes”?

And how about doing this yourself?

This is exactly what TonePrint allows you to do.

TC Electronic is working with top guitar players who explore a pedal's hidden tonal potential, redefining the controls and creating their personal TonePrints. And we are making these custom TonePrints available to you. Uploading them to your pedal is really easy (see “[Transferring TonePrints to your pedal using the TonePrint app](#)”) – and with the amazing TonePrint Editor, you can even create your own signature pedal, tweaked specifically to your liking.

You can change the TonePrint in your pedal as often as you like, and the best part:

It's totally free.

Transferring TonePrints to your pedal using the TonePrint app

Being able to virtually rewire your TC Electronic effect pedal wouldn't be much use if you needed a lot of extra equipment to do it. This is why we created the TonePrint app. The TonePrint app is free software for popular smartphones that allows you to “beam” new TonePrints right into your effect pedal whenever and wherever you feel like it.

Obtaining the TonePrint app

If you own an iPhone, you can download the TonePrint app from Apple's [App Store](#).

If you own an Android phone, you will find the TonePrint app on [Google Play](#).

Once you have the app, no additional downloads or in-app purchases are required. You can access all available TonePrints from within the app, and all TonePrints are free.

Transferring TonePrints to your pedal – step by step

- ▶ Launch the TonePrint app on your smartphone.
- ▶ Find the TonePrint you want to use. You can browse TonePrints by Artist or Product (i.e., pedal type). You will also find Featured TonePrints.
- ▶ Plug your guitar or bass into your TonePrint pedal.
- ▶ Turn your TonePrint pedal on.
- ▶ Turn up the volume on your instrument and set the pickup selector to one pickup.
- ▶ Hold the speaker of your smartphone next to the chosen pickup and touch “Beam to pedal”.

Editing TonePrints with TonePrint Editor

The TonePrint app allows you to use TonePrints created by your favorite guitar and bass players. But this is only the start. Using TC’s TonePrint Editor, you can create your very own signature pedal sounds.

TonePrint Editor features

- ▶ Use TonePrint Editor to build your own custom sounds.
- ▶ Enjoy complete control over all effect parameters and effect behavior – it’s your vision, your sound.
- ▶ Customize knob function and knob range to suit your needs and sounds.
- ▶ Audition your sonic creations in real-time live – make changes on the fly and listen to results immediately.
- ▶ Works with both PC and Mac.

Last but not least...

- ▶ TonePrint Editor is absolutely **free!**

Obtaining TonePrint Editor

If you want to use TonePrint Editor for your Windows or OS X computer, download it from

tcelectronic.com/toneprint-editor/

If you want to use TonePrint Editor on your Apple iPad, download it from Apple’s [App Store](#).

Please note that version 2.0 or higher of the TonePrint Editor is required for working with TC Electronic Mini pedals. Version 2.0 has a Library function that allows you to access and use TonePrints even without an Internet connection.

Obtaining the TonePrint Editor manual

Download the TonePrint Editor manual from

tcelectronic.com/toneprint-editor/support/

If you open the manual for TonePrint Editor in [Adobe Reader](#), you can click on interface sections to jump directly to the sections of the manual you are interested in.

Setup

Ready...

Your TC Electronic effect pedal box should contain the following items:

- ▶ Your TC Electronic effect pedal
- ▶ 1 USB cable (Type A to Mini-B)
- ▶ 1 TC Electronic sticker
- ▶ 1 leaflet about TC's guitar FX product range

Inspect all items for signs of transit damage. In the unlikely event of transit damage, inform the carrier and supplier.

If damage has occurred, keep all packaging, as it can be used as evidence of excessive handling force.

Set...

- ▶ Connect a 9 V power supply with the following symbol to the DC input socket of your TC Electronic effect pedal.



This product has no battery compartment. A power supply is required for operating this product.

This product does not come with a power supply. We recommend using TC Electronic's [PowerPlug 9](#) (sold separately).

- ▶ Plug the power supply into a power outlet.
- ▶ Connect your instrument to the in jack on the right side of the pedal using a ¼" jack cable.
- ▶ Connect the out jack on the left side of the pedal to your amplifier using a ¼" jack cable.

Play!

Inputs, outputs and controls



Hall of Fame Mini Reverb

Power / Switching the effect on and off

Power input

To power up your pedal, connect a power supply to its power input socket.

The power input socket of your TC Electronic effect pedal is a standard 5.5/2.1 mm DC plug (centre = negative).

Your TC Electronic effect pedal requires a 9 V power supply providing 100 mA or more (not supplied). TC Electronic recommends using the [PowerPlug 9](#).

To minimize hum, use a power supply with isolated outputs.

Footswitch

- ▶ To turn the effect on, tap the footswitch.
- ▶ To turn the effect off, tap the footswitch again.

Audio in and out

Audio input

The audio input on the *right* side of this pedal is a standard 1/4" jack (mono/TS).

- ▶ Connect your guitar to the audio input on the *right* side of your pedal using a regular 1/4" mono cable.

Audio output

The audio output on the *left* side of this pedal is a standard 1/4" jack (mono/TS).

- ▶ Connect the audio output of your pedal to the next device in the signal chain using a regular 1/4" mono cable.

USB port

Use the standard Mini-B USB port on your TC Electronic effect pedal to connect your pedal to a computer. This will allow you to load TonePrints into the pedal or create your own TonePrint using TC's TonePrint Editor. For more information, see ["TonePrint"](#).

If there should be firmware updates for this pedal, they can also be installed using the USB port – see ["Updating the firmware"](#).

Effect controls

Please note that the knob assignments on your TC Electronic effect pedal are the *default* assignments. Using the [TonePrint Editor](#), you can rewire all knobs so they control one or several parameters of your choice. For more information, see the [TonePrint Editor manual](#).

REVERB knob – Reverb level control

Use the Reverb knob to control the level of the reverb.

Please note that you can control parameters other than reverb level with the REVERB knob of your Hall of Fame Mini Reverb by using TC's [TonePrint Editor](#). The parameter assigned to the REVERB knob is stored as part of the TonePrint.

Reverb types

Getting started: popular Hall of Fame reverb TonePrints

This section of the manual describes some of the classic reverb types that you can transfer to your Hall of Fame Mini Reverb as described in ["Transferring TonePrints to your pedal using the TonePrint app"](#).

But remember that this is just the start: You can always create your personal reverb using the free [TonePrint Editor](#).

ROOM reverb

The Room reverb simulates a relatively small, well furnished room. In such a room, many reflections are absorbed by soft materials, and the sound is reflected and sustained only by the walls (covered with wallpaper), windows and maybe some furniture.

HALL reverb

The Hall reverb is a broad yet slightly diffuse reverb. It simulates a large environment but adds a distinctive acoustic flavor to the source material. Great discreet reverb for large epic sounds at longer decay settings but also perfect for genuine ambient sounds at shorter decay settings.

SPRING reverb

The Spring reverb has been designed to reproduce the sound of the old spring reverbs, such as the ones used in vintage guitar amps.

PLATE reverb

Prior to the digital era, reverb was created either using springs or large metallic plates. A plate reverb is recognized by its very diffuse and bright sound and is excellent for guitar when you search for a significant guitar reverb.

CHURCH reverb

Church reverb is a highly diffuse, large reverb that is recognizable for its emulation of the many hard surfaces of different shapes found in traditional church rooms. If you are looking for a large reverb and think the Hall is too clean and subtle – try Church.

MOD (Modulated) reverb

Early digital reverbs often sounded sterile and cold, so engineers used to add a chorus to the reverb to get a “warmer” sound. The Modulated reverb goes a step further and allows you to have different modulation effects on the reverb tail for even more tonal options. This reverb is really noticeable and cuts through in live situations.

LOFI (Low-Fi) reverb

Low-Fi reverb is a “down and dirty” reverb. Use Low-Fi and show your awareness of aiming in the straight opposite direction of the “smooth”, discrete studio reverb types. Make a statement!

TILE reverb

Use Tile reverb if you want that “bathroom” effect, without actually sounding like you’re playing

in your bathroom. Tile simulates the qualities of a small to medium size tiled room with its many reflections and at the same time it behaves respectfully towards the original source material. This is not a soft smooth reverb – this one cuts through the mix!

AMB (Ambient) reverb

Ambience is a cool, very short reverb that emulates the feeling of environment. Perfect to compensate for that desert-dry feeling of a close-miked cabinet.

GATE reverb

Gated is the classic reverb type typically heard on snare and kick drums on many Eighties recordings. A gate is used to rather abruptly shorten the reverb decay. Try it out – and stand out from the common usage of reverbs on guitar.

Maintenance

Updating the firmware

TC may provide updates for the built-in software of your pedal, the firmware. Updating your TC pedal's firmware requires...

- ▶ a computer running Microsoft Windows or OS X with a standard USB interface
- ▶ the specified DC power supply for your pedal.

Preparing the firmware update

- ▶ Download the newest firmware from the “Support” page for your TC pedal. There are updaters
 - for Microsoft Windows (these are ZIP archives containing the firmware installer) and
 - for OS X (these are disk image files containing the firmware installer).
- ▶ Unplug all cables (including the power supply) from your TC pedal.
- ▶ Connect the pedal to your computer using a USB cable.
- ▶ Press and hold the footswitch on your TC pedal. If your TC pedal has more than one footswitch, press and hold the leftmost footswitch.
- ▶ Insert the DC power supply plug.
- ▶ The LED on your pedal should turn green. If your TC pedal has more than one LED, the leftmost LED should turn green. This indicates that the pedal is ready to receive the software update.
- ▶ Release the footswitch.
- ▶ Your TC pedal will now be recognized as an updatable device.

Applying the firmware update

- ▶ Quit all MIDI-related applications (e.g. your DAW) on your computer and launch the firmware updater you have downloaded in step 1.
- ▶ In the firmware updater app, select your TC pedal from the drop-down list under the “STEP 1” heading.
- ▶ When the “Update” button under the “STEP 2” heading turns green, click it.

The updated firmware will now be transferred to your TC pedal. Wait for the progress bar to reach 100%. When the update procedure is complete, the pedal will automatically restart.

Frequently asked questions

Frequently asked questions about TonePrint pedals

“Are TonePrint pedals analog or digital?”

The dry signal of your guitar passes straight through this effect pedal and is in no way digitized. The “wet” signal is just added.

“Do the TonePrint pedals have balanced or unbalanced inputs/outputs?”

TonePrint pedals have unbalanced inputs and outputs. Use cables with TS jacks (i.e., standard instrument cables).

“Is it possible to run this TonePrint pedal in the effects loop of a tube amp?”

Yes. All TonePrint pedals have a very wide gain range and are designed to run at both instrument and line level. There are a few amps which are capable of running much hotter than regular +4 dBu line-level signals because of the way their effect loops are designed. With these amps, it might be possible to get the input to clip. But for 99 % of all amps, the TonePrint pedals will work just fine.

For additional information about your TC Electronic TonePrint effect pedal, please go to TC Electronic Support:

tcelectronic.com/support/

Links

TonePrint resources

- ▶ **TonePrint:**
tcelectronic.com/toneprint/
- ▶ **TonePrint products:**
tcelectronic.com/toneprint/toneprint-products/
- ▶ **TonePrint app:**
tcelectronic.com/toneprint-app/
- ▶ **TonePrint Editor:**
tcelectronic.com/toneprint-editor/
- ▶ **TonePrint Editor manual:**
tcelectronic.com/toneprint-editor/support/

Support resources

- ▶ **TC Electronic Support:**
tcelectronic.com/support/
- ▶ **TC Electronic – product software:**
tcelectronic.com/support/software/
- ▶ **TC Electronic – all product manuals:**
tcelectronic.com/support/manuals/
- ▶ **TC Electronic user forum:**
forum.tcelectronic.com/

TC Electronic on...

- ▶ **the web:**
tcelectronic.com/
- ▶ **Facebook:**
facebook.com/tcelectronic
- ▶ **Google Plus:**
plus.google.com/+tcelectronic/
- ▶ **Twitter:**
twitter.com/tcelectronic
- ▶ **YouTube:**
youtube.com/user/tcelectronic

Technical specifications

Please note that due to continuous development, the following specifications are subject to change without further notice.

Bypass mode	True Bypass
Signal circuitry	Analog dry-through
Dimensions (width x depth x height)	48 x 48 x 93 mm – 1.9 x 1.9 x 3.7"
Input connector	Standard ¼" jack – mono/TS
Output connector	Standard ¼" jack – mono/TS
Power input	Standard 9 V DC, centre negative >100 mA (power supply not included)
Battery option	-
Input impedance	1 MΩ
Output impedance	100 Ω
USB port	Mini USB connector for uploading and editing custom TonePrints and for software updates

